

Motor Kennzahl	Typ Type Tipo	KW 50 Hz		cos φ	%ED	S/h	J(10 ⁻³ kgm ²)	cos φA	1/min 50 Hz	I _N (A)				M _A /M _N		M _B /M _N		Absicherung(A) 3X50Hz			Zuleitungen					
		3X50Hz		500V						230V (ΔU 11,5V)	400V (ΔU 20V)	500V (ΔU 25V)														
		mm ²	m	mm ²	m	mm ²							m	mm ²	m	mm ²	m	mm ²	m							
ZH 4.1	ZFB100/4ZH132 Mc4x-12/2	1.25	0.50	50	180	45.536	0.55	460	13.8	8.0	6.1	1.8	1.32	3.57	25	16	16	2.5	>100	1.5	>100	1.5	>100			
		8.00	0.90			2860	0.70		29.4	17.0	12.9	5.3	1.50	3.74	63	35	25	10	35	4	42	2.5	43			
		1.00	0.48	60	240	45.536	0.55	470	13.0	7.5	5.7	2.0	1.57	4.47	25	16	16	2.5	>100	1.5	>100	1.5	>100			
		6.30	0.88			2880	0.70		24.2	14.0	10.6	6.4	1.89	4.71	63	35	25	10	32	4	39	2.5	43			
		0.80	0.54	60	300	45.536	0.55	475	13.0	7.5	5.7	2.0	2.00	5.72	25	16	16	2.5	>100	1.5	>100	1.5	>100			
		5.00	0.88			2900	0.70		19.0	11.0	8.4	8.1	2.38	5.96	63	35	25	10	33	4	40	2.5	43			
ZH 4.1		0.63	0.35	60	300	45.536	0.55	480	13.0	7.5	5.7	2.0	2.60	7.10	25	16	16	2.5	>100	1.5	>100	1.5	>100			
		4.00	0.80			2930	0.70		15.6	9.0	6.8	9.9	3.00	7.50	63	35	25	10	33	4	39	2.5	43			